

IG6
SET UP
PROCEDURE
(Message 8.80)

IG6 Set Up Procedure for Info Message 8.80

1. Preliminary

- a. Make sure all connections to LIM are properly attached.
- b. Supply power to IG6.
- c. Verify all alarms clear on the LIM within 15 seconds.
- d. Use IG6 operation Manual.

2. Set up (See figure 1 on page 3)

- a. Press "**Menu**" button for approx. 3 sec. to arrive at Menu Level 1.
- b. Using the "**Up**" or "**Down**" buttons, find "**4. Setting**" and press "**Menu**" to accept and be brought to Menu Level 2.
- c. If the IG6 is password protected follow steps below. If not, go to step "d".

Note: Default Password is 807

- i. When prompted to enter the password, use the "**Up**" and "**Down**" buttons to move along the numbers.
 - ii. When the desired number is shown, press "**menu**" to accept it and it will automatically send you to the following digit.
 - iii. After all 3 digits are completed; the screen will show "*Password OK*" and send you to the next level menu.
- d. Using the "**Up**" or "**Down**" buttons, find "**7. Clock**" and press "**Menu**" to accept and be brought to Menu Level 3.
 - e. Once on Menu Level 3, follow the steps below to reset the time and date parameters.
 - f. Press "**Menu**" and to edit each parameter using the "**Up**" or "**Down**" buttons, and pressing "**Menu**" to accept. To get back to the submenu, press "**menu**" until the submenu category starts flashing.
 - g. Once the "**Clock**" option has been selected click "**Menu**" to accept the "**Tim**" or Time option.
 - i. Use the "**Up**" or "**Down**" buttons to change the time.
 - ii. Hit "**Menu**" when desired hour is set and then select desired minute and click "**Menu**". Please Note: the "**A**", or AM, and "**P**", or PM, options for the time.
 - iii. Once your desired time is set press the "**Menu**" button.
 - h. Scroll down to the "**Dy**" or Date option and hit menu.
 - i. Use the "**Up**" or "**Down**" buttons to select desired month and click "**Menu**".
 - ii. Follow same steps for choosing the day.
 - iii. Once date is picked click the "**Menu**" button.
 - i. Scroll down once again to the "**Yr**" or Year option and click "**Menu**" to open this option.
 - i. Use the "**Up**" or "**Down**" buttons to select the correct year.
 - ii. Once year is selected click the "**Menu**" button.
 - j. Scroll down to the "**Exit**" option and click "**Menu**" to be brought back to Menu Level 2 and the "Clock" option on the LIM.
 - k. Once at the "Clock" option again scroll down to the "**Exit**" option and click "**Menu**" to be brought back Menu Level 1, the main option screen of the LIM.

Figure 1: IG6 Menu Structure

