

Micrologic control units

Overview of functions

All Compact circuit breakers are equipped with a Micrologic control unit that can be changed on site. Control units are designed to protect Power circuits and loads. Alarms may be programmed for remote indications.

Measurements of current, voltage, frequency, power and power quality optimise continuity of service and energy management.

Dependability

Integration of protection functions in an ASIC electronic component used in all Micrologic control units guarantees a high degree of reliability and immunity to conducted or radiated disturbances.

On Micrologic A, E and P control units, advanced functions are managed by an independent microprocessor.

Accessories

Certain functions require the addition of Micrologic control unit accessories, described on [page A-28](#).

The rules governing the various possible combinations can be found in the documentation accessible via the Products and services menu of the www.schneider-electric.com web site.

Micrologic without measurement	Measurements and programmable protection		
	A: ammeter ■ $I_1, I_2, I_3, I_N, I_{\text{earth-fault}}, I_{\text{earth-leakage}}$ and maximeter for these measurements ■ fault indications ■ settings in amperes and in seconds.		
	E: Energy ■ incorporates all the rms measurements of Micrologic A, plus voltage, power factor, power and energy metering measurements. □ calculates the current demand value □ "Quickview" function for the automatic cyclical display of the most useful values (as standard or by selection).		
	P: A + power meter + programmable protection ■ measurements of V, A, W, VAR, VA, Wh, VARh, VAh, Hz, $V_{\text{peak}}, A_{\text{peak}}$, power factor and maximeters and minimeters ■ IDMTL long-time protection, minimum and maximum voltage and frequency, voltage and current imbalance, phase sequence, reverse power ■ load shedding and reconnection depending on power or current ■ measurements of interrupted currents, differentiated fault indications, maintenance indications, event histories and time-stamping, etc.		

Micrologic name codes

2.0 E
X Y Z

X: type of protection

- 2 for basic protection
- 5 for selective protection
- 6 for selective + earth-fault protection
- 7 for selective + earth-leakage protection.

Y: control-unit generation

Identification of the control-unit generation.
"0" signifies the first generation.


Z: type of measurement

- A for "ammeter"
- E for "energy"
- P for "power meter"




Current protection

Micrologic 2: basic protection





Protection:
long time
+ instantaneous

Micrologic 5: selective protection





Protection:
long time
+ short time
+ instantaneous

Micrologic 6: selective + earth-fault protection



Protection:
long time
+ short time
+ instantaneous
+ earth fault

Micrologic 7: selective + earth-leakage



Protection:
long time
+ short time
+ instantaneous
+ earth leakage up to 3200A

2.0	2.0 A	2.0 E	
5.0	5.0 A	5.0 E	5.0 P
6.0	6.0 A	6.0 E	6.0 P
	7.0 A		7.0 P