

Procedure for applying voltage to an ATV after long duration storage.

As a function of the length of storage, you must re-apply voltage progressively to the product to re-form the capacitors. Calculate the storage time from the date code of the product and not from the date of delivery.

Storage time	Procedure to re-apply voltage
≤ 1 year	Apply voltage in the normal way
Between 1 and 2	Apply voltage to the product for 1 hour
≥ 2 years	Use a variable AC power supply to - 25% of nominal voltage for 30 - 50% of nominal voltage for 30 - 75% of nominal voltage for 30 - 100% of nominal voltage for 210