



P. O. BOX 20669
Sarasota, FL 34276

email sales@taylorphaseguard.com

Ph. 941 925-3605
Fax 800 288-7117

- ☐ **Model P** – On this device the master relay is normally ENERGIZED. When Conditions are normal and 3 phase power applied master relay connections are 1 to 2. When a phase loss occurs master relay will de-energize and contacts 1-3 will be closed. (1-2 will be open)
- ☐ **Model PND** – On this device the master relay is normally DE-ENERGIZED. When conditions are normal and 3 phase power applied master relay connections are 1to 3. When a phase loss occurs master relay will Energize and contacts 1-2 will be closed. (1-3 will be open)
- ☐ Time Delay Setting _____ Seconds ☐ Voltage Unbalance Setting _____%
- ☐ Adj. Phase loss Time Delay (Range .5 to 30 Sec.) **Adjust via Admin Tool software ONLY**
- ☐ Reverse Phase detection ☐ Normal relay selector (User select model P or PND operation)
- ☐ Low Voltage detection ☐ Low Voltage Trip Adj. (70-87%) & Time Delay (1-15 Sec.)
- ☐ Over Voltage detection ☐ Over Voltage Trip Adj. (108-115%) & Time Delay (1-15 Sec.)
- ☐ Reset Time delay (incl. Manual Reset)

We recommend this device be tested on a regular maintenance schedule.

SCREEN SAVER MODE begins after 10 minutes when voltage is normal
and cycles through the following

Normal – date & time / Last fault – date & time / “press any button to restore”

TO VIEW MODEL NUMBER - PRESS SELECT TWICE

After 5 seconds of no pushbutton input – display reverts to main screen.

MENU – via Pushbuttons

Press SELECT (Once) to enter **SETUP MENU** – you will see the following:

Version Info either (SELECT then SCROLL)
or
(SCROLL)

Model
Serial #
Firmware

Previous Events (SELECT then SCROLL)
or
(SCROLL)

Event log 1-50
Most recent to oldest
Updates automatically

Set Date Time (SELECT then SCROLL) * Day / Month / Year / Hour / Min.

*Any changes made automatically take effect after display reverts to main screen.

MENU – via **USB cable connection** go to

<http://taylorphaseguard.com/phaseguard/software.php> download ADMIN TOOL (PC & MAC)