

Example of Command from SCADA/IEC104 to a SC110/MODBUS to operate a switch

	Name	Description	Source1 Device	Source1 Coordinates	Source2 Device	Source2 Coordinates	Destination1 Device	Destination1 Coordinates
0	SC110_1_Open		I104S1	24577:CDC:C			SC110_1	CS:3936
1	SC110_1_Close		I104S1	24577:CDC			SC110_1	CS:3937
*								

Depending on the Switch Controller control logic:

- Using : **C** when a command is received from 104, depending on the value (1-ON or 2-OFF) only one command (Coil:3936 set to 1 or Coil:3937 set to 1) is sent to Modbus.
- Using : **CL** when a command is received from 104 the two commands Coil:3936 and Coil:3937 will be forced. One will be set to 1 and the other to 0 depending on the value of the double command from 104.