

what is the power loss per pole?

the table below indicates device power loss in Watts for each rating, per pole, with nominal current:

rating	0.5	0.75	1	1.6	2	2.5	3	4	6	6.3	10	12.5	16	20	25	32	40	50	63	80	100	125
circuit-breakers																						
DPN							2		3				3.4		3.7	4.7						
XC40							1.4		1.7				2		2.4	2.9	3.3					
C60	2.2	2.96	2.3		2.5		2.4	2.4	3		2		2.6		2.9	3	3.5	4.6	4.5	6.6		
C120										1.7		2.3	2.65	2.7	3.8	3.6	4.5	4.8	4.5	6	8	
NG125										2		2.5	3	3.2	3.5	4	4.7	5.5	6	7	9	
C60LMA				2.4		2.5		2.4	3	2	2.2	2.6		3		4.6						
NG125LMA								3	2	2		2.5	3	3.2	3.5	4	4.7	5.5	6	7	9	
switch																						
NG125NA																		5.5	6	7	9	
RCCB-ID												1		1.3		3.2		3.2	6	9		
I-NA																	3.2		3.2			

additional information