

Standard and Shallow Depth Light Modules

Table 19.274: Standard Light Modules for Types K, SK, and KX Control Units [121][122][123][124]

	Voltage	Description	Light Module	Voltage Assembly Code	Rating	Replacement Lamp
			Type [125]			Part Number [121]
	All	Full Voltage (without Bayonet Base Lamp)	KM40	40	—	None
	6 Vac/Vdc	Full Voltage	KM31	31	.9 VA	2550101020
	6 Vac/Vdc	LED Red	KM31LR	31LR		6508805201
	6 Vac/Vdc	LED Green	KM31LG	31LG		6508805203
	6 Vac/Vdc	LED Yellow	KM31LY	31LY		6508805202
	12–14 Vac/Vdc	Full Voltage	KM32	32	1.2 VA	2550101037
	12–14 Vac/Vdc	LED Red	KM32LR	32LR		6508805201
	12–14 Vac/Vdc	LED Green	KM32LG	32LG		6508805203
	12–14 Vac/Vdc	LED Yellow	KM32LY	32LY		6508805202
	18 Vac/Vdc	Resistor	KM33	33	1.4 VA	2550101037
	24–28 Vac/Vdc	Full Voltage	KM35	35	1.2 VA	2550101002
	24–28 Vac/Vdc	LED Red	KM35LR	35LR	.28 VA	6508805210
	24–28 Vac/Vdc	LED Green	KM35LG	35LG	.28 VA	6508805212
	24–28 Vac/Vdc	LED Yellow	KM35LY	35LY	.28 VA	6508805211
	24–28 Vac/Vdc	LED White	KM35LW	35LW	.28 VA	6508805214
	24–28 Vac/Vdc	LED Blue	KM35LL	35LL	.28 VA	6508805213
	48 Vac/Vdc	Full Voltage	KM36	36	2.6 VA	2550101025
	110–120 V, 50–60 Hz	LED Red	KM1LR	1LR		6508805201
	110–120 V, 50–60 Hz	LED Green	KM1LG	1LG		6508805203
	110–120 V, 50–60 Hz	LED Yellow	KM1LY	1LY		6508805202
	110–120 V, 50–60 Hz	Transformer	KM1	1	2.4 VA	2550101020
	110–120 V, 50–60 Hz	Flashing	KMF1	F1	.85 VA	2550101036
	120 Vac/Vdc	Full Voltage/Resistor	KM38	38	3.0 VA	2550101027
	120 Vac/Vdc	Neon [126]	KM11	11	0.2 VA	2550101013
	120 Vac/Vdc	LED Red	KM38LR	38LR	1.4 VA	6508805210
	120 Vac/Vdc	LED Green	KM38LG	38LG	1.4 VA	6508805212
	120 Vac/Vdc	LED Yellow	KM38LY	38LY	1.4 VA	6508805211
	120 Vac/Vdc	LED White	KM38LW	38LW	1.4 VA	6508805214
	120 Vac/Vdc	LED Blue	KM38LL	38LL	1.4 VA	6508805213
	208–220 V, 50–60 Hz	Transformer	KM3	3	2.5 VA	2550101020
	208–220 V, 50–60 Hz	LED Red	KM3LR	3LR		6508805201
	208–220 V, 50–60 Hz	LED Green	KM3LG	3LG		6508805203
	208–220 V, 50–60 Hz	LED Yellow	KM3LY	3LY		6508805202
	208–220 V, 50–60 Hz	LED White	KM3LW	3LW		6508805215
	208–220 V, 50–60 Hz	LED Blue	KM3LL	3LL		6508805216
	220–240 V, 50–60 Hz	Transformer	KM7	7	2.0 VA	2550101020
	220–240 V, 50–60 Hz	LED Red	KM7LR	7LR		6508805201
	220–240 V, 50–60 Hz	LED Green	KM7LG	7LG		6508805203
	220–240 V, 50–60 Hz	LED Yellow	KM7LY	7LY		6508805202
	220–240 V, 50–60 Hz	LED White	KM7LW	7LW		6508805215
	220–240 V, 50–60 Hz	LED Blue	KM7LL	7LL		6508805216
	240 Vac/Vdc	Resistor	KM25	25	6.0 VA	2550101027
	240 Vac/Vdc	Neon [126]	KM12	12	0.3 VA	2550101013
	277 V, 50–60 Hz	Transformer	KM8	8	2.4 VA	2550101020
	380–480 V, 50–60 Hz	Transformer	KM5	5	2.8 VA	2550101020
	480 Vac/Vdc	Neon [126]	KM14	14	0.5 VA	2550101013
	550–600 V, 50–60 Hz	Transformer	KM6	6	2.5 VA	2550101020

NOTE: Light modules are available in other voltages. For additional information, refer to Catalog 9001CT0001.

Table 19.275: Shallow Depth Light Modules For Types K and SK Control Units [121] [123] [127] [122]

	Voltage	Description	Light Module	Voltage Assembly Code	Rating	Replacement Lamp
			Type [125]			Part Number
	24–28 Vac/Vdc	Full Voltage	KM55	55	1.2 VA	2550101002
		LED Red	KM55LR	55LR		6508805204
		LED Green	KM55LG	55LG	0.5 VA	6508805206
		LED Yellow	KM55LY	55LY		6508805205
	110–120 Vac/Vdc	Full Voltage	KM58	58	3.0 VA	2550101027
		LED Red	KM58LR	58LR		6508805204
		LED Green	KM58LG	58LG	0.5 VA	6508805206
		LED Yellow	KM58LY	58LY		6508805205

File: E78403
CCN: NKCRFile: LR25490
Class: 3211 03

marked

[121] For use with all operators except KX and remote test pilot.

[122] For use in hazardous locations—See Square D Offering According to Class, Division, and Group, page 19-97.

[123] With LED light modules, use either a clear color cap or a cap the same color as the LED.

[124] With neon type light modules, use a clear color cap only.

[125] When ordering, add prefix 9001 to the catalog number.

[126] Not for use on KX operators.

[127] Reduces the depth of illuminated push buttons with contact blocks by over 33%.