

General Purpose Fuses IEC

Ferrule Fuses

gG 400V to 690V

with/without Striker

gG 8x32, 10x38, 14x51, 22x58

Power loss table

In	Size		
	10 x 38	14 x 51	22 x 58
0,5 A	2 W		
1 A	2,5 W	3,4 W	
2 A	0,70 W	1 W	1,20 W
4 A	0,80 W	1,10 W	1,30 W
6 A	0,90 W	1,20 W	1,40 W
8 A	1,10 W	1,50 W	1,65 W
10 A	1,35 W	1,80 W	2 W
12 A	1,55 W	2,10 W	2,40 W
16 A	1,90 W	2,55 W	3 W
20 A	2,30 W	3 W	3,40 W
25 A	2,80 W	3,50 W	3,80 W
32 A	3 W	3,80 W	4,30 W
40 A		4,40 W	5,10 W
50 A		4,7 W	5,50 W
63 A			6,70 W
80 A			8 W
100 A			9 W
125 A			12,5 W
IEC 269-2:1	10 x 38	14 x 51	22 x 58

Maximum standardized power loss.

General Purpose Fuses IEC

Ferrule Fuses

aM 400V to 690V

with/without Striker

aM 8x32, 10x38, 14x51, 22x58

Power loss table

In	Size		
	10 x 38	14 x 51	22 x 58
0,16 A	0,35 W		
0,25 A	0,50 W	0,70 W	
0,5 A	0,50 W	0,75 W	
1 A	0,13 W	0,18 W	0,20 W
2 A	0,20 W	0,25 W	0,30 W
4 A	0,30 W	0,40 W	0,50 W
6 A	0,45 W	0,55 W	0,65 W
8 A	0,55 W	0,65 W	0,75 W
10 A	0,65 W	0,75 W	0,85 W
12 A	0,75 W	0,85 W	1 W
16 A	0,90 W	1,20 W	1,40 W
20 A	1,10 W	1,50 W	1,70 W
25 A	1,40 W	1,80 W	2 W
32 A	2 W	2,10 W	2,60 W
40 A		2,60 W	3,20 W
45 A		2,80 W	
50 A		2,90 W	3,90 W
63 A			4,60 W
80 A			5,60 W